

NEW!

Dimax Int. GmbH (Germany) presents an updated version of the KS 4100iE inverter generator **with an ATS connection possibility.**

The updated KS 4100iE inverter generator from Könnér & Söhnen® features a possibility of connection for an external ATS unit (Automatic Transfer Switch). The generator control panel has an 8-pin ATS input that is compatible with the KS ATS 4/25 Gasoline ATS unit. The ATS unit automatically starts the generator and switches the load to it when the main power source is turned off.

The built-in electronic unit with microprocessor control monitors the operation of the generator and provides a stable output voltage of 230V 50Hz sinusoidal form, which is suitable for the reliable operation of sensitive electronics.

KS 4100iE

Max power/Nominal power, kW	4.0/3.6
Current (max), A	17.4
Outlets	2 x Schuko 230 V
Engine start	Manual/electric
Fuel tank volume, l	12.5
USB-Outputs	+
Input for ATS	+
Net dimensions (LxWxH), mm	530x410x430
Net weight, kg	36.7

KS 4100iE PROS:

- ✓ PURE SINE WAVE
- ✓ POSSIBILITY OF CONNECTING THE ATS SYSTEM (KS ATS 4/25 GASOLINE)
- ✓ ECONOMY MODE
- ✓ ROBUST ENGINE
- ✓ 3-IN-1 EASY ENGINE START
- ✓ LED DISPLAY
- ✓ TRANSPORTATION KIT

POWER
3.6 / 4.0
kW



Suitable for sensitive equipment

Robust engine K&S EURO 5

Operating status indicators

- Oil level indicator
- Overload indicator
- Voltage indicator

3-in-1 easy start system

Transport system

Output for ATS

Overload and short circuit protection

LED display (hour meter, voltage, frequency)

Two USB ports



TRADITIONS OF GERMAN QUALITY ARE AFFORDABLE FOR EVERYBODY!

