


 **NEW!**

Dimax Int. GmbH (Germany) presents an updated version of the KS 2000i S inverter generator in a brand new exclusive housing

The KS 2000i S inverter generator from Könnér & Söhnen® is a user-friendly and compact device with an integrated microprocessor unit, which makes it ideally suited for charging state-of-the-art sensitive equipment. Thanks to its compact design and a minimum noise level of only 62 dB (L_{pa} 7m), this model is extremely popular among tourists who prefer outdoor activities.

Moreover, a larger fuel tank means a longer running time without refueling.



PURE SINE WAVE

It ensures reliable operation of high-precision electronics, electronic measuring instruments, medical devices, heating boilers, etc.



ECONOMY MODE

The ECONOMY MODE enables to reduce fuel consumption by up to 50% at low loads through engine speed reduction.



PARALLEL CONNECTION

The KS PU1 unit increases the total output power of generators by connecting two inverter generators.



CONTROL PANEL

Display of all operating status indicators. USB ports for charging gadgets, LED display (hour meter, frequency, voltage).

KS 2000i S


Max/Nominal power	2.0/1.8 kW
Voltage/Frequency	230 V/50 Hz
Engine start	manual
Fuel tank volume	5 l
Sockets	1x16A (230 V)
LED display	+
Noise level L _{PA} (7m)/L _{WA}	62/87 dB
USB-Outputs	5B/1A, 5B/2.1A
Engine power	2.5 HP
Parallel connection output	+
Net dimensions (L x W x H)	480x280x460 mm
Net weight	19 kg



PURE SINE WAVE



ECONOMY MODE



The reliable branded K&S engine meets all European quality standards, including the latest EURO V emission standard.



TRADITIONAL GERMAN QUALITY IS AFFORDABLE FOR EVERYBODY!

